

Product Line
CR-RACK

Type
RM-CR-T1

Supported Models **CRADLEPOINT E300**

DIMENSIONS 1.3/2U

COLOR RAL 9005 Black


PRODUCT DIMENSIONS 57 x 482 x 217 mm

(height x width x depth) 2.24 x 18.98 x 8.54 in



MOUNTING INSTRUCTIONS

1. Optional: Remove the metal circles with a screwdriver and a hammer and connect the pigtails from the back of the CradlePoint to the round holes. Pigtails not provided.
2. Remove the 2 screws from the bottom of the appliance. One screw is located on the back left-hand side of the appliance and the other is located on the front right-hand side of the appliance.
3. Place your CradlePoint appliance on the rack.
4. Fix your appliance with the two M3x20 bolts from the bottom of the appliance.
5. Connect the power cable to the CradlePoint and secure the cable with the zip tie on the rack (detail 1).
6. Connect the cables from your CradlePoint to the connectors.
7. Optional: You can connect your own fiber patch cables to the SFP ports.
8. Optional: Use a zip tie to hold the cables together.
9. Place your CR-Rack in your 19-inch rack.
10. Place the Rackmount.IT front plate **BELOW** the CR-Rack in your 19 inch rack. Together they are 2U high.



Detail 1

Please ensure proper ventilation according to the network appliance manufacturer guidelines.

PACKAGE CONTENTS

Qty	Description
1	CR-rack
3	Zip ties
2	Bolts M3x20mm
5	Cables - 0.5 meter



**Consider the environment,
recycle where applicable.**

Rackmount.IT rack mount kits are RoHS compliant, developed & manufactured in the Netherlands and made of first quality parts.

In case of problems please contact your reseller or sales@rackmount.it.

Revision 1 31-03-2023

EMEA Office
Nonneveld 27
4811 HN Breda
The Netherlands
T +31 76 200 37 40
E sales@rackmount.it
WWW.RACKMOUNT.IT

US Office
9201 Metric Blvd - Unit A
Austin - TX 78758
United States
T +1 512 521 03 33
E sales-us@rackmount.it

RACKMOUNT.IT