

Product Line  
**FORTIDIN**

Type  
**RM-FR-D10B**  
**RM-FR-D10C**

# Supported Models

**FORTIGATE 60E/60E-POE**  
**FORTIGATE 60E-DSL**  
**FORTIGATE 60F/61E/61F**  
**FORTIGATE 70F/71F**

DIMENSIONS DIN Rail

COLOR RAL 9003 White

PRODUCT DIMENSIONS 89 x 235 x 221 mm  
(height x width x depth) 3.5 x 9.25x 8.7 in



## MOUNTING INSTRUCTIONS

1. Remove the 4 rubber feet from your FortiGate
2. Remove one of the two bottom screws of the FortiGate, the screws are located on the front side of the bottom. Make sure you do not break the seal on the second screw, breaking seals may void your Fortinet Warranty.
3. Connect the FortiDIN and FortiGate with the network cables. Make sure the cables are connecting the correct ports.
4. Connect the power supply and the grounding cable.
5. Place the unit in the rack and make sure the cables run free from the holder.
6. Put the allen key through the hole on the bottom of the FortiDIN, attach the bolt to the allen key, place your FortiGate in your FortiDIN and tighten the screw. Instruction video on web page.
7. Screw the screw-to-wire female connector to the screw-to-wire male connector.
8. Place your FortiDIN on your DIN-Rail

## PACKAGE CONTENTS

Qty	Description
1	FortiDIN
1	Bolt M3x6mm
1	Allen key
1	Screw-to-wire connector female
12	Cables - 0.5 meter



**Consider the environment,  
recycle where applicable.**

Rackmount.IT rack mount kits are RoHS compliant, developed & manufactured in the Netherlands and made of first quality parts.

In case of problems please contact your reseller or [sales@rackmount.it](mailto:sales@rackmount.it).

Revision 1 - 03-01-2022