

Product Line  
**WG-RACK**

Type  
**RM-WG-T7**  
**RM-WG-T7i**

Supported Models **WATCHGUARD**  
**FIREBOX T80**  
**FIREBOX T85**

DIMENSIONS 1.3/2U

COLOR WatchGuard Red

PRODUCT DIMENSIONS 57 x 482 x 217 mm  
(height x width x depth) 2.24 x 18.98 x 8.54 in



## MOUNTING INSTRUCTIONS

1. Place the power supply on the rack and tie it down with 2 zip ties.
2. Remove the 4 rubber feet from the WatchGuard.
3. Remove the bolt from the side of the appliance with the Torx key.
4. Place your WatchGuard unit on the rack and fix the unit with the provided bolt and tighten it lightly.
5. Tie the excess length of the power cable down with the 3rd zip tie.
6. Connect the cables from your WatchGuard to the connectors. Tip: start with the bottom row.
7. Optional: use two zip ties to hold the cables together.
8. Place your WG-Rack in your 19 inch rack.

Please ensure proper ventilation according to the network appliance manufacturer guidelines.

Please note that this unit is slightly higher than 1U.

## PACKAGE CONTENTS

Qty	Description
1	WG-Rack + RJ45 couplers
5	Zip ties
1	Torx key
1	Bolt 3x6mm
10	Cables - 0.5 meter



**Consider the environment,  
recycle where applicable.**

Rackmount.IT rack mount kits are RoHS compliant, developed & manufactured in the Netherlands and made of first quality parts.

In case of problems please contact your reseller or [sales@rackmount.it](mailto:sales@rackmount.it).

Industrial version is supplied with shielded couplers and cables

Revision 5 - 09-06-2021

EMEA Office  
Nonneveld 27  
4811 HN Breda  
The Netherlands  
T +31 76 200 37 40  
E [sales@rackmount.it](mailto:sales@rackmount.it)  
[WWW.RACKMOUNT.IT](http://WWW.RACKMOUNT.IT)

US Office  
9201 Metric Blvd - Unit A  
Austin - TX 78758  
United States  
T +1 512 521 03 33  
E [sales-us@rackmount.it](mailto:sales-us@rackmount.it)

**RACKMOUNT.IT**